

BA-7126-2

BA-7126-2

SIZE: 26'-0"L X 6'-6"H X 10"D

POWER: 120 VAC, 60 Hz., 1-PHASE

511 WATTS.

120 VAC AT THE CONTROL LOCATION.

CONTROL CONSOLE: MP-70 SERIES CONTROLLER.

CONTROL CABLE: 22GA 2-WIRE SHIELDED.

(IF WIRELESS ORDERED, CABLE NOT REQ'D.)

LEDs: AMBER LED.

OPTIONS: LIGHTNING DAMAGE REDUCTION UNIT.

WIRELESS MP-70 CONTROL OPERATION.

ACTUAL WEIGHT: 518 LBS.

GENERAL NOTES:

- * REFERENCE 01-0500-01 FOR INSTALLATION NOTES.
- * POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.

		CUSTOMER APPROVAL: I HAVE R	ture below signifies my approval to proceed with the des eceived and read the installation specifications contained y sales associate if you should have any questions or re	IN FAIR-PLAY DOCUMENT NO. 01-0500-01. CONSULT YOUR
		PROJECT:	SIGNATURE:	DATE:
_		REFERENCE #:	PRINT NAME:	
<u>'</u>	BEW		THE POSITIVE CONTAINS FAIR BLAY PROPRIETARY INFORMATION	ANY DISCUSSION LIST OF PURILICATION OF THE DOCUMENT
3	BEW	FAID-DLAY	THIS DOCUMENT CONTAINS FAIR—PLAY PROPRIETARY INFORMATION. OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN	THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS
ı I	DEW		EXPRESSLY PROHIBITED. EXCEPT AS MAY BE OTHERWISE AGREED	TO IN WRITING, COPYRIGHT 2022.

G	UPDATED TITLE BLOCK FORMAT	07-29-22	BEW	Ē
F	GENERAL UPDATES, FORMAT CHANGE	01-22-18	BEW	ı
E	UPDATED FACE VIEW IMAGE	08-07-13	BEW	ı
D	GENERAL UPDATES, POWER NOTE	02-02-12	BEW	ı
С	GENERAL UPDATES	03-24-11	BEW	
В	UPDATED POWER	04-01-10	RMS	l
Α	GENERAL UPDATES	09-11-07	BEW	ı
OR	ORIGINAL RELEASE	04-24-06	BEW	ı
REV.#	CHANGE	DATE	BY	

FACE VIEW FOR BA-7126-2

6110 AVIATOR DRIVE HAZELWOOD, MO 63042 | DRAWN BY | BEW | DATE | 04-24-06 | DWG NO

| 04-24-06 | DWG. NO. | SCALE | 3/8"=1'-0" | O1-7126-04-1