

BA-7126-2

## BA-7126-2

SIZE: 26'-0"L X 6'-6"H X 10"D

POWER: 120 VAC, 60 Hz., 1-PHASE 511 WATTS.

120 VAC AT THE CONTROL LOCATION.

CONTROL CONSOLE: MP-70 SERIES CONTROLLER. CONTROL CABLE: 22GA 2-WIRE SHIELDED.

(IF WIRELESS ORDERED, CABLE NOT REQ'D.)

LEDs: AMBER LED.

OPTIONS: LIGHTNING DAMAGE REDUCTION UNIT.

WIRELESS MP-70 CONTROL OPERATION.

ACTUAL WEIGHT: 518 LBS.

## **GENERAL NOTES:**

- \* REFERENCE 01-0500-01 FOR INSTALLATION NOTES.
- \* POWER REQUIREMENTS ARE VALID FOR 90 DAYS AFTER THE ORIGINAL RELEASE OR BY THE MOST RECENT REVISION OF THE DRAWING.

				CUSTOMER APPROVAL: I HAVE R	ECEIVED AND READ THE INSTALLATION SPECIFICATIONS CONTAIN Y SALES ASSOCIATE IF YOU SHOULD HAVE ANY QUESTIONS OF	
		_			SIGNATURE: PRINT NAME:	DATE:
Н	MOVED AT BAT DIGIT TO BE CENTERED	10-08-24	BEW	1121 21121102 W.	THE TWO THE	
G	UPDATED TITLE BLOCK FORMAT	07-29-22	BEW			
F	GENERAL UPDATES, FORMAT CHANGE	01-22-18	BEW		THIS DOCUMENT CONTAINS FAIR-PLAY PROPRIETARY INFORMATION. ANY DISCLOSURE, USE OR DUPLICATION OF THE DOCUMENT OR OF ANY INFORMATION CONTAINED THEREIN FOR OTHER THAN THE SPECIFIC PURPOSE FOR WHICH IT WAS DISCLOSED IS	
Ε	UPDATED FACE VIEW IMAGE	08-07-13	BEW		EXPRESSLY PROHIBITED, EXCEPT AS MAY BE OTHERWISE AGR	EED TO IN WRITING. COPYRIGHT 2022.
D	GENERAL UPDATES, POWER NOTE	02-02-12	BEW		TITLE FACE VIEW FOR	DRAWN BY MODEL
С	GENERAL UPDATES	03-24-11	BEW		FACE VIEW FOR	BEW   H   DA 7100 0
В	UPDATED POWER	04-01-10	RMS		BA-7126-2	DATE BA-7126-2
Α	GENERAL UPDATES	09-11-07	BEW		DA-7120-2	04-24-06 DWG, NO.
OR	ORIGINAL RELEASE	04-24-06	BEW	6110 AVIATOR DRIVE		SCALE O1 7100 01 1
REV.#	CHANGE	DATE	BY	HAZELWOOD, MO 63042		$ 3/8"=1'-0"  \cup  -/ 20-04- $